

# MONORAIL KITS WITH REMOTE TRANSFORMERS

location **DRY** 


## **SPECIFICATIONS:**

#### DESCRIPTION

Low voltage Monorail kits, complete with remote-mount power supply and support hardware. Monorail section is field-bendable without tools. 12V AC power output, 120V input.

### **RAIL KIT LENGTHS** includes:

- 04 4' Rail length, includes: 1x 4' Rail Section, 2x Rigid Standoff, 2x Rail Endcaps
- 08 8' Rail length, includes: 1x 8' Rail Section, 3x Rigid Standoff, 2x Rail Endcaps
- 12 12' Rail length, includes: 1x 8' Rail Section, 1x 4' Rail Section, 5x Rigid Standoff, 1x Live Rail Connector, 2x Rail Endcaps
- 16 16' Rail length, includes: 2x 8' Rail Section, 7x Rigid Standoff, 1x Live Rail Connector, 2x Rail Endcaps
- 20 20' Rail length, includes: 2x 8' Rail Section, 1x 4' Rail Section, 9x Rigid Standoff, 2x Live Rail Connector, 2x Rail Endcaps
- 24 24' Rail length, includes: 3x 8' Rail Section, 11x Rigid Standoff, 2x Live Rail Connector, 2x Rail Endcaps



## **REMOTE TRANSFORMERS:**

**REMFC** - Remote feed canopy ordered separately

RA60LED - 60W LED Electronic Remote Transformer, 120V

RA150 - 150W Electronic Remote Transformer, 120V


RA300 - 300W Electronic Remote Transformer, 120V

RM150 - 150W Magnetic Remote Transformer, 120V

RM300 - 300W Magnetic Remote Transformer, 120V

RA150LED - 150W LED Electronic Remote Transformer

RA300LED - 300W LED Electronic Remote Transformer





Electronic and magnetic transformer supports Besa halogen pendants or spotlights. *Not recommended for LED items.* 

For LED power supply, No-load 12V dimmable electronic transformer fits in the junction box. No remote transformer required. *Not recommended for standard halogen-lamped items* 

## **PENDANTS AND SPOTLIGHTS**

Order separately.

### **DIMMING**

Besa electronic remote transformers are compatible with low voltage electronic dimmers. Besa magnetic remote transformers are compatible with a high-quality low voltage magnetic dimmer.

### **METAL FINISH**

Black or Satin Nickel.

**Project Information:** 

#### **MOUNTING**

Transformer canopy installs directly to a 4"octagonal ceiling box. All mounting hardware included. Not suitable for sloped ceilings.

#### LABELS

UL or ETL Listed. Suitable for Dry Locations (interior use only).

## **ORDERING:**

SYSTEM -	SYSTEM - LENGTH		1	POWER TRANSFORMER		ŀ	ME	TAL FINISH
R12 Monorail System	04	4' Length		REMFC	Remote Feed Canopy ordered separately		BK	Black
	08	8' Length		RA60LED	60W LED Electronic Remote Transformer		SN	Satin Nicke
	12	12' Length		RA150	150W Electronic Remote Transformer			
	16	16' Length		RA300	300W Electronic Remote Transformer			
	20	20' Length		RM150	150W Magnetic Remote Transformer			
	24	24' Length		RM300	300W Magnetic Remote Transformer			
				RA150LED	150W LED Electronic Remote Transformer			
				RA300LED	300W LED Electronic Remote Transformer			

Ex. R12-08-RA60LED-SN

8' Monorail kit with 60W LED Remote Transformer in Satin Nickel.

All dimensions provided are nominal.

Allowance must be made for dimensional tolerance in handcrafted glasses.

**REV 8/25**