GLASS SHADE INSTALLATION GUIDE

Model J Series - (Med. Base Pendant Set 120V)

Rope Pendant, Rev.2 10-16



6695 Taylor Rd. Blacklick, OH 43004 www.besalighting.com

Use With these Models:	IMPORTANT: For installation of pendants and wiring, please refer to the Fixture Installation Guide included with fixture canopy
• Sultana (SULTANA)	 Carefully unpack parts. Remove Mounting Plate (A) from Canopy (B), by unthreading Cap Nuts (C) from the Threaded posts (H).
	 Intall the Mounting Plate (A) to the Outlet Box (D), as shown. Feed the Fixture Cord (E) through the Canopy (B) and connect House Supply Wires to Fixture Cord Conductors as follows: House Ground Wire to Green Conductor Cord, Black to Black and White to White with provided Wirenuts (F). Install Rope (G) to Canopy (A) by hooking Rope (G) to Canopy (A), then push wires and wirenuts into the Outlet Box (D).
	 Align the openings on the canopy with the Threaded Posts on the Mounting Plate. Push the Canopy (B) up over the Threaded Posts until tight to the ceiling, then secure with the two Cap Nuts (C).
	4. Proceed to shade installation.

All electrical connections and the installation of this fixture must be in agreement with local codes, ordinances or the NEC (National Electric Code) or CEC (Canadian Electrical Code). Do not connect this fixture to an electrical system that does not provide a means for equipment grounding.

SHADE INSTALLATION GUIDE

Model J Series - (Med. Base Pendant Set 120V)



6695 Taylor Rd. Blacklick, OH 43004 www.besalighting.com

Use With these Models:	IMPORTANT: For installation of pendants and wiring, please refer to the Fixture Installation Guide included with fixture canopy
• Sultana (SULTANA)	1. Install lamp then Secure Shade per the diagram.
	2. Restore power.
	Decorative Posts
	NOTE: Shade is for instructional purposes. Actual Shade may vary in size and shape.
ſ	POLARITY INSTRUCTIONS SOCKET
	SCREWSHELL
	Using a Continuity Tester or Multimeter, confirm the following connections:
	Clear Conductor with White Stripe (Neutral/White) is connected to the Socket Screwshell. This wire is to be connected to house supply white conductor.
	Clear Conductor (Hot/Black) is connected to the Socket Center Contact. This wire is to be connected to house supply black wire. SOCKET CENTER CONTACT
C	All electrical connections and the installation of this fixture must be in agreement with local codes, ordinances or the NEC (National Electric Code) or CEC (Canadian Electrical Code)

ordinances or the NEC (National Electric Code) or CEC (Canadian Electrical Code). Do not connect this fixture to an electrical system that does not provide a means for equipment grounding.